

IBM TotalStorage DS4500



Excellent performance and scalability

The IBM TotalStorage® DS4500 (formerly FAStT900 Storage Server) is a member of the IBM TotalStorage DS4000 series. The DS4500 is an enterprise-class storage server that is designed to provide performance and flexibility for today's demanding data-intensive computing environments.

The DS4000 EXP710 switched disk expansion unit has an ESM-imbedded Fibre Channel "loop switch." The loop switch creates what is essentially point-to-point Fibre Channel communication, allowing the ESMs and drives to operate as though they were on a private Fibre Channel arbitrated loop, but with the performance and diagnostic advantages of Fibre Channel fabric. A great advantage of the DS4000 EXP710 is a significant reduction in the number of Fibre Channel nodes on the drive loops. The DS4000 EXP710 has far fewer nodes on the drive loop than the DS4000 EXP700.

Highlights

- **Uses 2GB Fiber Channel connectivity (up to 795 MBps throughput from disk) for fast, responsive access to data**
- **Facilitates storage consolidation for storage area network, network attached storage and direct-attach storage environments**
- **Offers optional, advanced replication functions such as IBM FlashCopy®, VolumeCopy and Enhanced Remote Mirror**
- **Supports 2GB Fiber Channel (FC) and Serial ATA disk drive modules**
- **Supports 2 to 224 hard disk drives and provides more than 67TB of FC scalability or 89.6TB of Serial ATA scalability**
- **Includes IBM TotalStorage DS4000 Storage Manager to help manage the storage subsystem**

The DS4500 offers more than 67TB of fibre channel disk storage capacity with the DS4000 EXP710 or DS4000 (EXP700) or up to 89.6TB of Serial ATA storage capacity with DS4000 EXP100. The DS4500 is well-suited for high-performance applications such as online transaction processing (OLTP), data mining and digital media when attached to the DS4000 EXP710 or DS4000 (EXP700).

The DS4500 builds on the capabilities of existing DS4000 series systems, using a common storage management interface and similar disk expansion tools. It attaches to DS4000 EXP710, DS4000 (EXP700) and DS4000 EXP100 disk enclosures, and can support up to 224 Fibre Channel disk drives when using 16 DS4000 EXP710 or 16 DS4000 (EXP700) disk enclosures. It can support up to 224 Serial ATA disk drives when using 16 DS4000 EXP100 disk enclosures. When combined with DS4000 EXP710 or DS4000 (EXP700) disk enclosures and 2GB IBM TotalStorage SAN Switches, the DS4500 can be used to help build a complete 2GB SAN environment.

In addition, the performance capabilities of the DS4500 exceed those of other DS4000 series systems, with up to 795 MBps disk throughput. It also uses advanced caching algorithms to help optimize disk performance.

The DS4500 supports IBM @server® pSeries®, xSeries® and BladeCenter™ servers as well as other popular Intel® processor-based, AIX® and UNIX® operating system-based servers and operating systems.

Enhanced storage management capabilities

The IBM TotalStorage DS4500 has several features designed to facilitate data management and improve storage system performance. IBM TotalStorage DS4000 Storage Manager Software is designed to centralize storage management, which can help allow administrators to be more productive. In addition, administrators can partition the DS4500 into as many as 64 virtual servers. This capability allows organizations to strategically allocate storage capacity, helping to maximize storage space and reduce hardware and storage management costs.

Another feature of the DS4500 is Dynamic Volume Expansion, which is designed to allow administrators to resize logical volumes without disrupting other services within the storage system. This feature can help administrators expand storage while maintaining high data availability.

DS4000 Intermix feature for attachment of Fiber Channel and Serial ATA Disk Storage Expansion Units

The IBM TotalStorage DS4500, DS4400 and DS4300 Turbo Mid-range Disk Systems with this new feature have the capability to support attachment of both DS4000 EXP710 Fibre and DS4000 (EXP700) Channel Disk Expansion units and DS4000 EXP100 Serial ATA Disk Expansion units concurrently. This feature requires the DS4500, DS4400, or DS4300 Turbo systems be upgraded to the DS4000 Storage Manager V9.10 firmware (06.10 or later) and host-based code (SM V9.10 or later). With this feature, you can create

and manage distinct array groups that are built from either FC disks or SATA disks and allocate logical drives to the appropriate applications utilizing a single DS4000 system. Those applications that demand high performance and have high I/O rates could use the FC-based drives, while near-line, or applications that do not demand the high performance of FC-based drives can be maintained on the SATA based-drives..

Improved productivity through DS4000 Storage Manager

IBM TotalStorage DS4000 Storage Manager Software is designed to provide centralized, online management of local or remote DS4000 series. DS4000 Storage Manager allows administrators to configure and monitor storage from a Java™ technology-based Web browser interface. It is also designed to allow them to customize and change settings

on the fly as well as configure new volumes, define mappings, tune performance, handle routine maintenance and dynamically add new enclosures, disk drives and capacity to existing data volumes.

By providing an intuitive user interface and reducing the complexity of storage management, this software tool can help reduce the amount of time spent managing storage, helping companies to lower costs.

Additional tools to help manage storage

Other IBM tools can be used in conjunction with DS4000 Storage Manager to help manage storage on the DS4500.

IBM FlashCopy® is an optional feature that is designed to create an immediate single-point-in-time copy of all stored data that requires only a fraction of the original disk space. The fully functional

snapshot volume can be used for file restoration, backups, application testing or data mining – all while the primary volume is active.

Another optional feature supported with V9.1 is Enhanced Remote Mirror. It consists of Global Mirror with Asynchronous Write-order Consistency, which is critical for mirroring multi-LUN applications, Global Copy with Asynchronous, and Metro Mirror with Synchronous.

VolumeCopy is an optional feature designed to provide the ability to create a full VolumeCopy of a point-in-time logical drive generated by FlashCopy on a single DS4000. This option requires DS4000 Storage Manager version 8.4 or later.

IBM TotalStorage DS4500 at a glance

Characteristics

Model	1742-90U
RAID controller	Dual active 2GB RAID controllers
Cache	2GB, battery-backed
Host interface	Fibre Channel (FC) Switched and FC Arbitrated Loop (FC-AL)
Connectivity	4 standard, up to 8 via additional mini-hubs
Drive interface	FC-AL
Supported drives	36.4GB, 73.4GB, 146.8GB 10,000 rpm and 300GB 10,000 rpm (2GB FC) 18.2GB, 36.4GB, 73.4GB 15,000 rpm and 146.8GB 15,000 rpm (2GB FC) 400GB 7200 rpm (SATA), 250GB 7200 rpm (SATA)
RAID levels	0, 1, 3, 5, 10
Storage partitioning	16, upgradeable to 64
Maximum drives supported	224 (using 16 DS4000 EXP100 or 16 DS4000 EXP700 or 16 DS4000 EXP710 Expansion Units)
Fans and power supplies	Dual redundant, hot-swappable
Rack support	19-inch, industry-standard rack
Management software ¹	IBM TotalStorage DS4000 Storage Manager version 8.3, 8.4, 8.41 or 9.1, 9.14, 9.15
SAN support	Supported IBM FC switches and directors (product numbers 2109, 3534, 2031, 2032, 2042 and 2062)
Optional copy services	FlashCopy, VolumeCopy
Availability features	Enhanced Remote Mirroring
Certifications	Microsoft® Cluster Server (MSCS), Novell Clustering, HACMP, VERITAS Cluster for Solaris and MC/Service Guard
Warranty	3-year parts and labor warranty, next-business-day response; upgradeable to 24x7 support with 4-hour response

Physical characteristics

Dimensions	174.5 mm H x 482 mm W x 635 mm D (6.87 in x 18.97 in x 24 in)
Weight	43.9 kg (97 lbs)

Supported systems²

For a list of currently supported servers, operating systems, host bus adapters, clustering applications and SAN switches and directors, refer to the DS4500 interoperability matrix available at ibm.com/storage/ds4500. For availability dates, configuration options, and attachment capabilities, refer to: ibm.com/storage/ds4500

IBM DS4000 EXP100 Expansion Unit

Model	1710-10U
Number of drives supported	Up to 14 Serial ATA 400GB 7200 rpm, 250GB 7200 rpm
Fans and power supplies	Dual redundant, hot-swappable
Dimensions (with bezel)	13.23 cm H x 48.18 cm W x 59.74 cm D (5.21 in x 18.97 in x 23.52 in)

IBM DS4000 EXP700 Expansion Unit

Model	1740-1RU
Number of drives supported	Up to 14 FC drives (18.2GB, 36.4GB, 73.4GB, 146.8GB or 300GB)
Fans and power supplies	Dual redundant, hot-swappable
Dimensions (with bezel)	13.23 cm H x 48.18 cm W x 59.74 cm D (5.21 in x 18.97 in x 23.52 in)

IBM DS4000 EXP710 Expansion Unit

Model	1740-710
Number of drives supported	Up to 14 FC drives (18.2GB, 36.4GB, 73.4GB, 146.8GB or 300GB)
Fans and power supplies	Dual redundant, hot-swappable
Dimensions (with bezel)	13.23 cm H x 48.18 cm W x 59.74 cm D (5.21 in x 18.97 in x 23.52 in)

For more information

Contact your IBM representative,
IBM Business Partner or visit:

ibm.com/totalstorage/ds4500



MB, GB and TB equal 1,000,000, 1,000,000,000 and 1,000,000,000,000 bytes, respectively, where referring to storage capacity. Actual storage capacity will vary based upon many factors and may be less than stated. Some numbers given for storage capacities give capacity in native mode followed by capacity using data compression technology.

THE INFORMATION IN THIS DOCUMENT IS PROVIDED "AS-IS" WITHOUT ANY WARRANTY, EITHER EXPRESSED OR IMPLIED. IBM EXPRESSLY DISCLAIMS ANY WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR INFRINGEMENT. IBM products are warranted according to the terms and conditions of the agreements (e.g., IBM Customer Agreement, Statement of Limited Warranty, International Program License Agreement, etc.) under which they are provided.

References in this document to IBM products, programs or services does not imply that IBM intends to make such products, programs or services available in all countries in which IBM operates or does business. Any reference to an IBM program or product in this document is not intended to state or imply that only that program may be used. Any functionally equivalent program or product that does not infringe IBM's intellectual property rights may be used instead. It is the user's responsibility to evaluate and verify the operation of any non-IBM product, program or service.

¹ IBM TotalStorage DS4000 Storage Manager V8.41 firmware is required for DS4000 EXP100 (SATA) support. For additional information and configuration details, please refer to **ibm.com**/storage/ds4500

² For specific details and configuration availability, please visit **ibm.com**/storage/ds4500.

© Copyright IBM Corporation 2005

IBM Systems and Technology Group
9000 Rita Road
Tucson, AZ 85744

Produced in the United States
October 2005
All Rights Reserved

IBM, the IBM logo, the e-business logo, AIX, BladeCenter, @server, FlashCopy, pSeries, TotalStorage and xSeries are trademarks of International Business Machines Corporation in the United States, other countries, or both.

Intel is a trademark of Intel Corporation in the United States, other countries, or both.

Microsoft, Windows and Windows NT are trademarks of Microsoft Corporation in the United States, other countries, or both.

Java, Solaris and Sun are trademarks of Sun Microsystems, Inc. in the United States, other countries, or both.

UNIX is a registered trademark of The Open Group in the United States and other countries.

Other company, product and service names may be trademarks or service marks of others.

This document could include technical inaccuracies or typographical errors. IBM may make changes, improvements or alterations to the products, programs and services described in this document, including termination of such products, programs and services, at any time and without notice. Any statements regarding IBM's future direction and intent are subject to change or withdrawal without notice, and represent goals and objectives only. The information contained in this document is current as of the initial date of publication only and is subject to change without notice. IBM shall have no responsibility to update such information.

IBM is not responsible for the performance or interoperability of any non-IBM products discussed herein. Performance data for IBM and non-IBM products and services contained in this document was derived under specific operating and environmental conditions. The actual results obtained by any party implementing such products or services will depend on a large number of factors specific to such party's operating environment and may vary significantly. IBM makes no representation that these results can be expected or obtained in any implementation of any such products or services.